

Part Number: BN10-0179-C06-1


Description: BNC Crimp Jack

To suit cable types: Belden 1522A, RG179PE

Strip Dimensions

A=12mm, B=3mm, C=3mm

Cable Preparation



■ Assembly Instructions

1) Slide the ferrule onto the cable and strip the cable to the dimensions as shown, taking care not to nick the centre conductor or braid.



2) Open the cable braid and slide the insulator tube over the dielectric and under the braid. Crimp the contact onto the centre core and slide the contact into the body until it captivates, ensuring that the cable braid is on the outside of the connector mandril.



3) Slide the ferrule forward and crimp.



Recommended Crimp Tool(s): GCT-0058 DCC1113

Crimp Hex. Sizes: 5.41mm Hex., 1.69mm Hex.