

**Part Number: BN10-3002-C06-2**

*Description:* BNC Crimp Jack

*To suit cable types:* BT3002, TZC75024

*Strip Dimensions*

A=8mm, B=3mm, C=3mm

*Cable Preparation*



**Assembly Instructions**


1) Slide the ferrule onto the cable and strip the cable to the dimensions as shown, taking care not to nick the centre conductor or braid.



2) Crimp the contact onto the centre core and slide the contact into the body until it captivates, ensuring that the cable braid is on the outside of the connector mandril.



3) Slide the ferrule forward and crimp.



*Crimp Hex. Sizes:* 4.52mm Hex., 1.46mm Hex.