

Part Number: MX10-0174-C01


Description: MCX Crimp Jack, Gold Plated

To suit cable types: AMC-174, LBC100, LBC100 LSZH, LMR100, RG174, RG188, RG316, WBC100

Strip Dimensions

A=5mm, B=2.5mm, C=2.5mm

Cable Preparation



■ Assembly Instructions

1) Slide the ferrule onto the cable and strip the cable to the dimensions as shown, taking care not to nick the centre conductor or braid.



2) Crimp the contact onto the centre core and slide the contact into the body, ensuring that the cable braid is on the outside of the connector mandril and that the contact is fully located.



3) Slide the ferrule forward and crimp.



Recommended Crimp Tool(s): GCT-D316 PCC0308

Crimp Hex. Sizes: 3.25mm Hex., 0.72mm Square