


Part Number: NT02-0174-C06-12

Description: N Type Crimp Bulkhead Jack, Nickel Plated
To suit cable types: RG174, RG188, RG316, LBC100

Strip Dimensions

A=8mm, B=5mm, C=8mm

Cable Preparation




■ **Assembly Instructions**

1) Slide the ferrule onto the cable and strip the cable to the dimensions as shown, taking care not to nick the centre conductor or braid. Tin the centre conductor of the cable.



2) Slide the centre conductor into the contact assembly, ensuring that the cable braid is on the outside of the connector mandril and that the conductor is in as far as possible. Crimp the ferrule, then solder the conductor through the solder hole in the contact.



3) Slide contact through the insulator and screw contact assembly into body until tight.



Recommended Crimp Tool(s): GCT-D316 PCC0308

Crimp Hex. Sizes: 3.25mm Hex., Solder centre core