


**Part Number: NT02-0174-C06-2**

*Description:* N Type Crimp Bulkhead Jack, Nickel Plated  
*To suit cable types:* LBC100, LBC100 LSZH, RG174, RG188, RG316

*Strip Dimensions*  
 A=9.5mm, B=1.5mm, C=3.5mm

*Cable Preparation*



■ Assembly Instructions

1) Slide the ferrule onto the cable and strip the cable to the dimensions as shown, taking care not to nick the centre conductor or braid.



2) Slide the tube onto the cable and under the braid, then slide the insulator onto the centre core. Crimp the pin onto the centre core and slide the pin into the body until it is fully located, ensuring that the cable braid is on the outside of the connector mandril.



3) Slide the ferrule forward and crimp.



*Recommended Crimp Tool(s):* GCT-0058 DCC1113  
*Crimp Hex. Sizes:* 5.41mm Hex., 1.69mm Hex.